

MODERN DIGITAL MULTIMETER

Model Number : GOTT-DT9205A



DESCRIPTION

The GOTT-DT9205A is one of the most common items of test equipment used in the electronics industry today.

While there are many other items of test equipment that are available, the GOTT-DT9205A is able to provide excellent readings of the basic measurements of amps, volts and ohms.

In addition to this the fact that these modern digital multimeter use digital and logic technology, means that the use of integrated circuits rather than analogue techniques, enables many new test features to be embedded in the design.

Digital multimeter is a great tool for electricians, contractors, and other such professions as well as being a handy tool to have around the house for home repair.

* Proposed design only, subject to changes without any notice.

SPECIFICATIONS

- 100% brand new and high quality
- Measure AC/ DC voltage, AC/ DC current, resistance, capacitance and diode
- Power Supply: 9V battery(Not included)
- Large LCD display with high accuracy
- Dimension:186mm*86mm*33mm
- Comes with one black test lead and one red test lead
- Stable performance, high reliability
- Max LCD display: 1999
- Operating condition: 0 to 40
- Weight: 380g
- LCD display panel angle selection: with the button in the top case, the display panel can be rotated to the best angle

GENERAL SPECIFICATIONS :

FUNCTION	RANGE	ACCURACY	RESOLUTION	FUNCTION	RANGE	ACCURACY	RESOLUTION
• DC Vol.	200mV	+-(0.5%+3d)	0.1mV	• DC Amp.	2mA	+-(1.0%+5d)	0.001mA
	2v	+-(0.8%+2d)	1mV		20mA		0.01mA
	20v		10mV		200mA		0.1mA
	200v	0.1V	20A		+-(2.0%+10d)	10mA	
	1000v	+-(0.8%+4d)	0.5V	• Resistance	200 Ω	+-(1.0%+10d)	0.1 Ω
• AC Vol.	200mV	+-(1.2%+5d)	0.1mV	2K Ω	+-(1.0%+4d)	1 Ω	
	2V	+-(1.0%+5d)	1mV	20K Ω		10 Ω	
	20V		10mV	200K Ω		100 Ω	
	200V		0.1V	2M Ω		1k Ω	
	750V	+-(1.2%+5d)	0.375V	20M Ω	+-(1.0%+5d)	10k Ω	
• AC Amp.	2mA	+-(2.0%+3d)	0.001mA	200M Ω	+-(5.0%+20d)	100k Ω	
	20mA		0.01mA	• Capacitance	20nF	+-(4.0%+5d)	0.01nF
	200mA	+-(2.0%+5d)	0.1mA	200nF	0.1nF		
	20A	+-(3.0%+10d)	10mA	2μF	1nF		
• Diode	Forward current:1Ma (Approx) ; Reverse voltage:2.8V			20μF	10nF		
				200μF	+-(5.0%+10d)	100nF	

Manuals :

- (1) All manuals are written in English
- (2)Teaching Manuals

General Terms :

- (1) Accessories will be provided where applicable.
- (2) Manual & Training will be provided where applicable.
- (3) Design & specifications are subject to change without notice.
- (4) We reserve the right to discontinue the manufacturing of any product.

Warranty :

2 Years

ITEM	MODEL NUMBER	CODE
MODERN DIGITAL MULTIMETER	GOTT-DT9205A	461-000

* Proposed design only, subject to changes without any notice.